

BC-5000-12

BATTERY CHARGER



The TOA BC-5000-6 and BC-5000-12 are dedicated battery chargers for the WM-5225 and WM-5265 Wireless Microphones, WM-5325 Wireless Transmitter, and the WT-5100 Portable Receiver. Both chargers work with the optional AD-5000-6 AC Adapter. The BC-5000-6 and BC-5000-12 employ a quick charging system for nickel-metal hydride (Ni-MH) batteries, allowing up to 6 or 12 units to be fully charged within 3 hours.

Key features

- Charging station for the transmitters of the 5000 series
- Up to 12 transmitters can be fully recharged in only 3 hours

Specifications

Power Source	12 V DC (optional AC adapter AD-5000-6 must be used)
Current Consumption	4.4 A
Charging Time	Max. 3 h
Number of Units to be Charged Simultaneously	12 pieces
Operating Temperature	0 # to +40 # (32 # to 104 #)
Operating Humidity	30 % to 85 %RH (no condensation)
Finish	Case: Steel plate, black, paint Microphone receptacle section: ABS resin, black
Dimensions	390 (W) x 118 (H) x 246 (D) mm (15.35" x 4.65" x 9.69") (including mounting adapter)
Weight	3.4 kg (7.5 lb) (charger with the mounting adapters attached)
Included Accessories	Mounting adapter ...12
Optional Accessories	Rechargeable battery: WB-2000-2 (containing 2 pieces) AC adapter: AD-5000-6

