

S4.10-RXA-AMRM3

Trantec S4.10 Wireless Receiver



The Trantec S4.10-RXA desktop receiver is available on channel 38, or license free channel 70. Up to ten Trantec S4.10 systems can be used simultaneously, which allows use in education, theater, gym, and hotel sectors.

Key features

- Up to 16 selectable frequencies (Up to 16 Simultaneous channels)
- IR Sync - Infrared auto channel setup
- Phase-lock-look (PLL) quartz tuning
- Frequency scan function
- Numerical LED display

Specifications

Power Source	1 AA size alkaline battery 1.5V
Mixing Input	Audio Input Level: 140dB SPL (maximum)
Frequency Response	80Hz – 15kHz
Battery	1 AA size alkaline battery 1.5V
Battery Life	Approx. 10 hours
Finish	Resin, coating
Dimensions	250 x 55mm
Weight	245g (with battery)